

Communication cycle **0.0625 ms**

Ultra-high-speed network driver

RTEX
Realtime Express

Realtime Express(RTEX)

AC servo motor & driver

MINAS A6N Series




INDEX

| | |
|-----------------------------------|-----|
| Features..... | 349 |
| Advantages of RTEX..... | 351 |
| Model designation..... | 353 |
| Driver appearance..... | 354 |
| System configuration..... | 354 |
| Table of parts numbers..... | 355 |
| Driver..... | 359 |
| Driver common specifications..... | 359 |
| Dimensions of driver..... | 363 |
| Options..... | 368 |
| Interface cable..... | 368 |
| Interface connector Kit..... | 368 |

Pursuit of ultimate real-time processing

Pursuit of ultimate real-time processing



●Max.4 Mpps,when using AB-phase external scale

Multifunctional capabilities to match various needs

- ◎ Supports all positions, speeds and torque modes (w/built-in positioning function)
- ◎ High-precision position latch and comparison
- ◎ Communication cycle can be set to any time between 2 ms and 62.5 μs.

● Easy setup with setup support software "PANATERM".

Simple network

- ◎ Satisfies both high performance and low cost requirements
- ◎ Synchronization established by communication IC
- ◎ Easier development of compatible equipment


* For options other than for Interface cable and connector kit for interface, see P.29 to P.42.

● Realtime Express and RTEX are registered trademarks of Panasonic Holdings Corporation..

●The "Conventional I/F" used in this document means a pulse train and analog I/F.


Wire-saving

Wire-saving reduces various troubles relating to wires. The cables used are widely available Ethernet cables, which are easy to obtain and inexpensive.




Maximum length of the node-to-node cable is 100 m.

Flexibility increases in the layout of an upper controller and servo motors. The RTEXs can also support large-scale systems.



Configurable parameter settings

Upper controllers can configure servo parameters. This enables parameters to be configured automatically instead by human at installation.




Real time monitoring is enabled.

Upper controllers can monitor various information, such as position, speed, and torque, etc. in real time. Since alarm codes can also be read out, analysis can be performed promptly at trouble occurrence.



Up to 32 axes can be controlled.


In comparison with conventional I/Fs, the number of axes increases that can be controlled by next upper controllers.



* If devices other than servo motors are also connected, up to 32 nodes can be connected as entire slaves including the servo motors. Actual number of controllable axes depends on the specification of an upper controller.


Profile position mode is supported

Profile position mode is supported for PTP control as well as cyclic position, speed, and torque. The processing done by upper controllers can be simplified.



High synchronization capability among axes


Upper controllers synchronize with entire servo motor axes at high accuracy. With the synchronization capability higher than that of conventional I/F, the RTEX is best suitable for machine tools, robots, gantry systems, and others.



* Interpolation depends on the specification of upper controllers. This is not the function of individual servo motor.


Absolute system can easily be built.

Conventional I/F requires an additional wire to transmit absolute data, while the RTEX doesn't. Each servo motor synthesizes one-revolution data and multi-revolution data to produce an actual position, so that the amount of work to be done by an upper controller is decreased.



High resolution command is enabled


The position command rate of max. 8 Mpps* in a pulse train I/F is improved to 4 Gpps* in the RTEX. Vibrations are reduced due to a smooth command sent to a servo motor using the advantage of the high-resolution encoder.



* Max. 8 Mpps is a rate when A6 servo driver is used. Max. 4 Gpps is a rate when A6N servo driver is used.

High noise-proof property

With a patented error correction function, noise-proof property is at least 2.5 KV. This conforms to IEC61000-4-4 standard.



* The error correction function has a limit. Unrecovered broken data causes a communication error.

* For combination of elements of model number, refer to Index P.411.

Servo Motor

M S M F 5 A Z L 1 A 1 * — Special specifications

① Type

| Symbol | Type |
|--------|------------------------------------|
| MSM | Low inertia (50 W to 5.0 kW) |
| MQM | Middle inertia (100 W to 400 W) |
| MDM | Middle inertia (1.0 kW to 22.0 kW) |
| MGM | Middle inertia (0.85 kW to 5.5 kW) |
| MHM | High inertia (50 W to 7.5 kW) |

② Series

| Symbol | Series name |
|--------|-------------|
| F | A6 Family |

⑦ Motor specifications: 80 mm sq. or less MSMF 50 W to 1000 W

| Symbol | | Shaft | | Holding brake | | Oil seal | | Motor encoder terminal ¹⁾ | |
|--------|---|-------|---------------------|---------------|------|----------|------|--------------------------------------|-----------|
| | | Round | Key-way, center tap | without | with | without | with | Connector JN | Lead wire |
| A | 1 | ● | | ● | | ● | | ● | |
| A | 2 | ● | | ● | | ● | | ● | |
| B | 1 | ● | | ● | | ● | | ● | |
| B | 2 | ● | | ● | | ● | | ● | |
| C | 1 | ● | | ● | | ● | | ● | |
| C | 2 | ● | | ● | | ● | | ● | |
| D | 1 | ● | | ● | | ● | | ● | |
| D | 2 | ● | | ● | | ● | | ● | |
| S | 1 | ● | ● | ● | | ● | | ● | |
| S | 2 | ● | ● | ● | | ● | | ● | |
| T | 1 | ● | ● | ● | | ● | | ● | |
| T | 2 | ● | ● | ● | | ● | | ● | |
| U | 1 | ● | ● | ● | | ● | | ● | |
| U | 2 | ● | ● | ● | | ● | | ● | |
| V | 1 | ● | ● | ● | | ● | | ● | |
| V | 2 | ● | ● | ● | | ● | | ● | |

③ Motor rated output

| Symbol | Rated output | Symbol | Rated output | Symbol | Rated output |
|--------|--|--------|--------------|--------|--------------|
| 5A | 50 W | 13 | 1.3 kW | 44 | 4.4 kW |
| 01 | 100 W | 15 | 1.5 kW | 50 | 5.0 kW |
| 02 | 200 W | 18 | 1.8 kW | 55 | 5.5 kW |
| 04 | 400 W | 20 | 2.0 kW | 75 | 7.5 kW |
| 08 | 750 W | 24 | 2.4 kW | C1 | 11.0 kW |
| 09 | 0.85 kW, 1000 W (130 mm sq.) (80 mm sq.) | 29 | 2.9 kW | C5 | 15.0 kW |
| | | 30 | 3.0 kW | D2 | 22.0 kW |
| 10 | 1.0 kW | 40 | 4.0 kW | | |

④ Voltage specifications

| Symbol | Specifications |
|--------|--------------------------------|
| 1 | 100 V |
| 2 | 200 V |
| Z | 100 V/200 V common (50 W only) |

⑥ Design order

| Symbol | Specifications |
|--------|----------------|
| 1 | Standard |

<Note>
When using a rotary encoder as an incremental system (not using multi-turn data), do not connect a battery for absolute encoder.

⑤ Rotary encoder specifications

| Symbol | Format | Pulse counts | Resolution | Wires |
|--------|----------|--------------|------------|-------|
| L | Absolute | 23-bit | 8388608 | 7 |

⑦ Motor specifications: IP67²⁾ 100 mm sq. to 220 mm sq. MSMF, MHMF, MDMF, MGMF

| Symbol | Shaft | | Holding brake | | Oil seal | | Encoder terminal | |
|--------|-------|---------|---------------|------|----------|---------------------|----------------------------|---|
| | Round | Key-way | without | with | with | With protective lip | Connector JN2 (Small size) | Connector JL10 (Large size) ³⁾ |
| C | 5 | ● | ● | | ● | | ● | |
| C | 6 | ● | ● | | ● | | ● | |
| C | 7 | ● | ● | | ● | | ● | |
| C | 8 | ● | ● | | ● | | ● | |
| D | 5 | ● | ● | | ● | | ● | |
| D | 6 | ● | ● | | ● | | ● | |
| D | 7 | ● | ● | | ● | | ● | |
| D | 8 | ● | ● | | ● | | ● | |
| G | 5 | ● | ● | | ● | | ● | |
| G | 6 | ● | ● | | ● | | ● | |
| G | 7 | ● | ● | | ● | | ● | |
| G | 8 | ● | ● | | ● | | ● | |
| H | 5 | ● | ● | | ● | | ● | |
| H | 6 | ● | ● | | ● | | ● | |
| H | 7 | ● | ● | | ● | | ● | |
| H | 8 | ● | ● | | ● | | ● | |

⑦ Motor specifications: 80 mm sq. or less MHMF 50 W to 1000 W MQMF 100 W to 400 W

| Symbol | | Shaft | | Holding brake | | Oil seal | | Motor encoder terminal ¹⁾ | |
|--------|---|-------|---------------------|---------------|------|----------|------|--------------------------------------|--------------|
| | | Round | Key-way, center tap | without | with | without | with | With protective lip | Connector JN |
| A | 1 | ● | | ● | | ● | | ● | |
| A | 2 | ● | | ● | | ● | | ● | |
| B | 1 | ● | | ● | | ● | | ● | |
| B | 2 | ● | | ● | | ● | | ● | |
| C | 1 | ● | | ● | | ● | | ● | |
| C | 2 | ● | | ● | | ● | | ● | |
| C | 3 | ● | | ● | | ● | | ● | |
| C | 4 | ● | | ● | | ● | | ● | |
| D | 1 | ● | | ● | | ● | | ● | |
| D | 2 | ● | | ● | | ● | | ● | |
| D | 3 | ● | | ● | | ● | | ● | |
| D | 4 | ● | | ● | | ● | | ● | |
| S | 1 | ● | ● | ● | | ● | | ● | |
| S | 2 | ● | ● | ● | | ● | | ● | |
| T | 1 | ● | ● | ● | | ● | | ● | |
| T | 2 | ● | ● | ● | | ● | | ● | |
| U | 1 | ● | ● | ● | | ● | | ● | |
| U | 2 | ● | ● | ● | | ● | | ● | |
| U | 3 | ● | ● | ● | | ● | | ● | |
| U | 4 | ● | ● | ● | | ● | | ● | |
| V | 1 | ● | ● | ● | | ● | | ● | |
| V | 2 | ● | ● | ● | | ● | | ● | |
| V | 3 | ● | ● | ● | | ● | | ● | |
| V | 4 | ● | ● | ● | | ● | | ● | |

*1 Connector type: IP67, Lead wire type: IP65 *2 22.0 kW: IP44
*3 Connector on the motor side encoder. (Also applicable to screwed type.)

Servo Driver

M A D L N 1 5 N E * * * — Special specifications

① Frame symbol

| Symbol | Frame | Symbol | Frame |
|--------|---------|--------|---------|
| MAD | A-Frame | MED | E-Frame |
| MBD | B-Frame | MFD | F-Frame |
| MCD | C-Frame | MGD | G-Frame |
| MDD | D-Frame | MHD | H-Frame |

② Series

| Symbol | Series name |
|--------|-------------|
| L | A6 Family |

③ Safety Function⁴⁾

| Symbol | Specifications |
|--------|-----------------------------|
| N | without the safety function |
| T | with the safety function |

④ Max. current rating

| Symbol | Current rating | Symbol | Current rating |
|--------|----------------|--------|----------------|
| 0 | 6 A | 9 | 80 A |
| 1 | 8 A | A | 100 A |
| 2 | 12 A | B | 120 A |
| 3 | 22 A | C | 160 A |
| 4 | 24 A | E | 240 A |
| 5 | 40 A | F | 360 A |
| 8 | 60 A | | |

⑤ Supply voltage specifications


| Symbol | Specifications |
|--------|----------------------|
| 1 | Single phase 100 V |
| 3 | 3-phase 200 V |
| 5 | Single/3-phase 200 V |

⑥ I/f specifications

| Symbol (specification) | Symbol | Specification |
|------------------------|--------|---|
| N (RTEX) | E | Standard for rotary motor |
| | F | Multifunction for rotary motor |
| | L | Standard for linear/DD motor Special Order Product |
| | M | Multifunction for linear/DD motor Special Order Product |


*4 Standard type (with a part number ending in E or L) has no safety function. Multi-function type (with a part number ending in F or M) has a safety function.

Appearance



* The photo is A6NF series. There are no X3 and X5 connectors in the A6NE series.

Typical system configuration



*1: The communication period and connection of slave devices depend on the controller specification.
*2: For communication period 0.0625 ms, command update period is 0.125 ms only.

● 80 mm sq. or less 50 W to 1000 W MSMF, MQMF, MHMF Leadwire type IP65

| Motor | | | | Driver | | Power capacity (at rated load) |
|--|-----------------------------------|------------|----------------|---------------------|-----------------|--------------------------------|
| Motor series | Power supply | Output (W) | Part No. | A6N series Part No. | Dimension Frame | |
| MSMF (Leadwire type) 3000 r/min Low inertia | Single phase 100 V | 50 | MSMF5AZL1 □ 2 | MADL☆01N☆ | A-frame | Approx. 0.4 kVA |
| | | 100 | MSMF011L1 □ 2 | MADL☆11N☆ | | |
| | | 200 | MSMF021L1 □ 2 | MBDL☆21N☆ | B-frame | |
| | | 400 | MSMF041L1 □ 2 | MCDL☆31N☆ | C-frame | |
| | Single phase/ 3-phase 200 V | 50 | MSMF5AZL1 □ 2* | MADL☆05N☆ | A-frame | Approx. 0.5 kVA |
| | | 100 | MSMF012L1 □ 2* | | | |
| | | 200 | MSMF022L1 □ 2* | MADL☆15N☆ | | |
| | | 400 | MSMF042L1 □ 2* | MBDL☆25N☆ | B-frame | |
| | | 750 | MSMF082L1 □ 2* | MCDL☆35N☆ | C-frame | |
| | | 1000 | MSMF092L1 □ 2* | MDDL☆45N☆ | D-frame | |
| MQMF (Leadwire type) 3000 r/min Middle inertia Flat type | Single phase 100 V | 100 | MQMF011L1 □ □ | MADL☆11N☆ | A-frame | Approx. 0.4 kVA |
| | | 200 | MQMF021L1 □ □ | MBDL☆21N☆ | B-frame | Approx. 0.5 kVA |
| | | 400 | MQMF041L1 □ □ | MCDL☆31N☆ | C-frame | Approx. 0.9 kVA |
| | Single phase/ 3-phase 200 V | 100 | MQMF012L1 □ □* | MADL☆05N☆ | A-frame | Approx. 0.5 kVA |
| | | 200 | MQMF022L1 □ □* | MADL☆15N☆ | | |
| | | 400 | MQMF042L1 □ □* | MBDL☆25N☆ | | |
| MHMF (Leadwire type) 3000 r/min High inertia | Single phase 100 V | 50 | MHMF5AZL1 □ □ | MADL☆01N☆ | A-frame | Approx. 0.4 kVA |
| | | 100 | MHMF011L1 □ □ | MADL☆11N☆ | | |
| | | 200 | MHMF021L1 □ □ | MBDL☆21N☆ | B-frame | |
| | | 400 | MHMF041L1 □ □ | MCDL☆31N☆ | C-frame | |
| | Single phase/ 3-phase 200 V | 50 | MHMF5AZL1 □ □* | MADL☆05N☆ | A-frame | Approx. 0.5 kVA |
| | | 100 | MHMF012L1 □ □* | | | |
| | | 200 | MHMF022L1 □ □* | MADL☆15N☆ | | |
| | | 400 | MHMF042L1 □ □* | MBDL☆25N☆ | B-frame | |
| | | 750 | MHMF082L1 □ □* | MCDL☆35N☆ | C-frame | |
| | | 1000 | MHMF092L1 □ □* | MDDL☆55N☆ | D-frame | |

□ ☆ * : For more information, refer to "Model Designation" on P.353.

● 80 mm sq. or less 50 W to 1000 W MSMF, MQMF, MHMF Connector type IP67

| Motor | | | | Driver | | Power capacity (at rated load) |
|---|-----------------------------------|------------|---------------|---------------------|-----------------|--------------------------------|
| Motor series | Power supply | Output (W) | Part No. | A6N series Part No. | Dimension Frame | |
| MSMF (Connector type) 3000 r/min Low inertia | Single phase 100 V | 50 | MSMF5AZL1 □ 1 | MADL☆01N☆ | A-frame | Approx. 0.4 kVA |
| | | 100 | MSMF011L1 □ 1 | MADL☆11N☆ | | |
| | | 200 | MSMF021L1 □ 1 | MBDL☆21N☆ | B-frame | |
| | | 400 | MSMF041L1 □ 1 | MCDL☆31N☆ | C-frame | |
| | Single phase/ 3-phase 200 V | 50 | MSMF5AZL1 □ 1 | MADL☆05N☆ | A-frame | Approx. 0.5 kVA |
| | | 100 | MSMF012L1 □ 1 | | | |
| | | 200 | MSMF022L1 □ 1 | MADL☆15N☆ | | |
| | | 400 | MSMF042L1 □ 1 | MBDL☆25N☆ | B-frame | |
| | | 750 | MSMF082L1 □ 1 | MCDL☆35N☆ | C-frame | |
| | | 1000 | MSMF092L1 □ 1 | MDDL☆45N☆ | D-frame | |
| MQMF (Connector type) 3000 r/min Middle inertia Flat type | Single phase 100 V | 100 | MQMF011L1 □ □ | MADL☆11N☆ | A-frame | Approx. 0.4 kVA |
| | | 200 | MQMF021L1 □ □ | MBDL☆21N☆ | B-frame | Approx. 0.5 kVA |
| | | 400 | MQMF041L1 □ □ | MCDL☆31N☆ | C-frame | Approx. 0.9 kVA |
| | Single phase/ 3-phase 200 V | 100 | MQMF012L1 □ □ | MADL☆05N☆ | A-frame | Approx. 0.5 kVA |
| | | 200 | MQMF022L1 □ □ | MADL☆15N☆ | | |
| | | 400 | MQMF042L1 □ □ | MBDL☆25N☆ | | |
| MHMF (Connector type) 3000 r/min High inertia | Single phase 100 V | 50 | MHMF5AZL1 □ □ | MADL☆01N☆ | A-frame | Approx. 0.4 kVA |
| | | 100 | MHMF011L1 □ □ | MADL☆11N☆ | | |
| | | 200 | MHMF021L1 □ □ | MBDL☆21N☆ | B-frame | |
| | | 400 | MHMF041L1 □ □ | MCDL☆31N☆ | C-frame | |
| | Single phase/ 3-phase 200 V | 50 | MHMF5AZL1 □ □ | MADL☆05N☆ | A-frame | Approx. 0.5 kVA |
| | | 100 | MHMF012L1 □ □ | | | |
| | | 200 | MHMF022L1 □ □ | MADL☆15N☆ | | |
| | | 400 | MHMF042L1 □ □ | MBDL☆25N☆ | B-frame | |
| | | 750 | MHMF082L1 □ □ | MCDL☆35N☆ | C-frame | |
| | | 1000 | MHMF092L1 □ □ | MDDL☆55N☆ | D-frame | |

□ ☆ : For more information, refer to "Model Designation" on P.353.

● 100 mm sq. or more 0.85 kW to 5.0 kW MSMF, MDMF, MGMF, MHMF
Encoder connector (Large size JL10)^{*1} type IP67

| Motor | | | | Driver | | Power capacity (at rated load) |
|--|--------------------------------|------------|----------------|---------------------|-----------------|--------------------------------|
| Motor series | Power supply | Output (W) | Part No. | A6N series Part No. | Dimension Frame | |
| MSMF (Large size JL10 type) 3000 r/min Low inertia IP67 | Single phase/ 3-phase 200 V | 1000 | MSMF102L1 □□ * | MDDL☆55N☆ | D-frame | Approx. 2.9 kVA |
| | | 1500 | MSMF152L1 □□ * | | | |
| | 3-phase 200 V | 2000 | MSMF202L1 □□ * | MEDL☆83N☆ | E-frame | Approx. 3.8 kVA |
| | | 3000 | MSMF302L1 □□ * | MFDL☆A3N☆ | F-frame | Approx. 5.2 kVA |
| | | 4000 | MSMF402L1 □□ * | MFDL☆B3N☆ | | Approx. 7.8 kVA |
| 5000 | MSMF502L1 □□ * | | | | | |
| MDMF (Large size JL10 type) 2000 r/min Middle inertia IP67 | Single phase/ 3-phase 200 V | 1000 | MDMF102L1 □□ * | MDDL☆45N☆ | D-frame | Approx. 2.4 kVA |
| | | 1500 | MDMF152L1 □□ * | MDDL☆55N☆ | E-frame | Approx. 2.9 kVA |
| | 3-phase 200 V | 2000 | MDMF202L1 □□ * | MEDL☆83N☆ | | Approx. 3.8 kVA |
| | | 3000 | MDMF302L1 □□ * | MFDL☆A3N☆ | Approx. 5.2 kVA | |
| | | 4000 | MDMF402L1 □□ * | MFDL☆B3N☆ | Approx. 7.8 kVA | |
| 5000 | MDMF502L1 □□ * | | | | | |
| MGMF (Large size JL10 type) [Low speed/ High torque type] 1500 r/min Middle inertia IP67 | Single phase/ 3-phase 200 V | 850 | MGMF092L1 □□ * | MDDL☆45N☆ | D-frame | Approx. 2.4 kVA |
| | | 1300 | MGMF132L1 □□ * | MDDL☆55N☆ | E-frame | Approx. 2.9 kVA |
| | 3-phase 200 V | 1800 | MGMF182L1 □□ * | MEDL☆83N☆ | | Approx. 3.8 kVA |
| | | 2400 | MGMF242L1 □□ * | MEDL☆93N☆ | Approx. 4.5 kVA | |
| | | 2900 | MGMF292L1 □□ * | MFDL☆B3N☆ | Approx. 7.8 kVA | |
| 4400 | MGMF442L1 □□ * | | | | | |
| MHMF (Large size JL10 type) 2000 r/min High inertia IP67 | Single phase/ 3-phase 200 V | 1000 | MHMF102L1 □□ * | MDDL☆45N☆ | D-frame | Approx. 2.4 kVA |
| | | 1500 | MHMF152L1 □□ * | MDDL☆55N☆ | E-frame | Approx. 2.9 kVA |
| | 3-phase 200 V | 2000 | MHMF202L1 □□ * | MEDL☆83N☆ | | Approx. 3.8 kVA |
| | | 3000 | MHMF302L1 □□ * | MFDL☆A3N☆ | Approx. 5.2 kVA | |
| | | 4000 | MHMF402L1 □□ * | MFDL☆B3N☆ | Approx. 7.8 kVA | |
| 5000 | MHMF502L1 □□ * | | | | | |

□ ☆ * : For more information, refer to "Model Designation" on P.353.

● 100 mm sq. or more 0.85 kW to 5.0 kW MSMF, MDMF, MGMF, MHMF
Encoder connector (Small size JN2)^{*2} type IP67

| Motor | | | | Driver | | Power capacity (at rated load) |
|---|--------------------------------|------------|--------------|---------------------|-----------------|--------------------------------|
| Motor series | Power supply | Output (W) | Part No. | A6N series Part No. | Dimension Frame | |
| MSMF (Small size JN2 type) 3000 r/min Low inertia IP67 | Single phase/ 3-phase 200 V | 1000 | MSMF102L1 □□ | MDDL☆55N☆ | D-frame | Approx. 2.9 kVA |
| | | 1500 | MSMF152L1 □□ | | | |
| | 3-phase 200 V | 2000 | MSMF202L1 □□ | MEDL☆83N☆ | E-frame | Approx. 3.8 kVA |
| | | 3000 | MSMF302L1 □□ | MFDL☆A3N☆ | F-frame | Approx. 5.2 kVA |
| | | 4000 | MSMF402L1 □□ | MFDL☆B3N☆ | | Approx. 7.8 kVA |
| 5000 | MSMF502L1 □□ | | | | | |
| MDMF (Small size JN2 type) 2000 r/min Middle inertia IP67 | Single phase/ 3-phase 200 V | 1000 | MDMF102L1 □□ | MDDL☆45N☆ | D-frame | Approx. 2.4 kVA |
| | | 1500 | MDMF152L1 □□ | MDDL☆55N☆ | E-frame | Approx. 2.9 kVA |
| | 3-phase 200 V | 2000 | MDMF202L1 □□ | MEDL☆83N☆ | | Approx. 3.8 kVA |
| | | 3000 | MDMF302L1 □□ | MFDL☆A3N☆ | Approx. 5.2 kVA | |
| | | 4000 | MDMF402L1 □□ | MFDL☆B3N☆ | Approx. 7.8 kVA | |
| 5000 | MDMF502L1 □□ | | | | | |
| MGMF (Small size JN2 type) [Low speed/ High torque type] 1500 r/min Middle inertia IP67 | Single phase/ 3-phase 200 V | 850 | MGMF092L1 □□ | MDDL☆45N☆ | D-frame | Approx. 2.4 kVA |
| | | 1300 | MGMF132L1 □□ | MDDL☆55N☆ | E-frame | Approx. 2.9 kVA |
| | 3-phase 200 V | 1800 | MGMF182L1 □□ | MEDL☆83N☆ | | Approx. 3.8 kVA |
| | | 2400 | MGMF242L1 □□ | MEDL☆93N☆ | Approx. 4.5 kVA | |
| | | 2900 | MGMF292L1 □□ | MFDL☆B3N☆ | Approx. 7.8 kVA | |
| 4400 | MGMF442L1 □□ | | | | | |
| MHMF (Small size JN2 type) 2000 r/min High inertia IP67 | Single phase/ 3-phase 200 V | 1000 | MHMF102L1 □□ | MDDL☆45N☆ | D-frame | Approx. 2.4 kVA |
| | | 1500 | MHMF152L1 □□ | MDDL☆55N☆ | E-frame | Approx. 2.9 kVA |
| | 3-phase 200 V | 2000 | MHMF202L1 □□ | MEDL☆83N☆ | | Approx. 3.8 kVA |
| | | 3000 | MHMF302L1 □□ | MFDL☆A3N☆ | Approx. 5.2 kVA | |
| | | 4000 | MHMF402L1 □□ | MFDL☆B3N☆ | Approx. 7.8 kVA | |
| 5000 | MHMF502L1 □□ | | | | | |

□ ☆ * : For more information, refer to "Model Designation" on P.353.

● 176 mm sq. or more 5.5 kW or more MDMF, MGMF, MHMF
Encoder connector (Large size JL10)^{*1} type IP67

| Motor | | | | Driver | | Power capacity (at rated load) |
|--|------------------|---------------------|-----------------|---------------------|-----------------|--------------------------------|
| Motor series | Power supply | Output (W) | Part No. | A6N series Part No. | Dimension Frame | |
| MDMF (Large size JL10 type) 1500 r/min Middle inertia IP67 ^{*3} | 3-phase 200 V | 7500 | MDMF752L1 □ 6 * | MGDLTC3NF | G-frame | Approx. 11 kVA |
| | | 11000 | MDMFC12L1 □ 6 | MHDLTE3NF | H-frame | Approx. 15 kVA |
| | | 15000 | MDMFC52L1 □ 6 | MHDLTE3NF | | Approx. 20 kVA |
| | | 22000 ^{*3} | MDMFD22L1 □ 6 | MHDLTF3NF | Approx. 28 kVA | |
| MGMF (Large size JL10 type) [Low speed/ High torque type] 1500 r/min Middle inertia IP67 | 3-phase 200 V | 5500 | MGMF552L1 □ 6 * | MGDLTC3NF | G-frame | Approx. 8.5 kVA |
| MHMF (Large size JL10 type) 1500 r/min High inertia IP67 | 3-phase 200 V | 7500 | MHMF752L1 □ 6 * | MGDLTC3NF | G-frame | Approx. 11 kVA |


□ ☆ * : For more information, refer to "Model Designation" on P.353.

● 176 mm sq. or more 5.5 kW or more MDMF, MGMF, MHMF
Encoder connector (Small size JN2)^{*2} type IP67


| Motor | | | | Driver | | Power capacity (at rated load) |
|---|------------------|---------------------|---------------|---------------------|-----------------|--------------------------------|
| Motor series | Power supply | Output (W) | Part No. | A6N series Part No. | Dimension Frame | |
| MDMF (Small size JN2 type) 1500 r/min Middle inertia IP67 ^{*3} | 3-phase 200 V | 7500 | MDMF752L1 □ 5 | MGDLTC3NF | G-frame | Approx. 11 kVA |
| | | 11000 | MDMFC12L1 □ 5 | MHDLTE3NF | H-frame | Approx. 15 kVA |
| | | 15000 | MDMFC52L1 □ 5 | MHDLTE3NF | | Approx. 20 kVA |
| | | 22000 ^{*3} | MDMFD22L1 □ 5 | MHDLTF3NF | Approx. 28 kVA | |
| MGMF (Small size JN2 type) [Low speed/ High torque type] 1500 r/min Middle inertia IP67 | 3-phase 200 V | 5500 | MGMF552L1 □ 5 | MGDLTC3NF | G-frame | Approx. 8.5 kVA |
| MHMF (Small size JN2 type) 1500 r/min High inertia IP67 | 3-phase 200 V | 7500 | MHMF752L1 □ 5 | MGDLTC3NF | G-frame | Approx. 11 kVA |

□ ☆ * : For more information, refer to "Model Designation" on P.353.

*1: Encoder connector (Large size JL10)



*2: Encoder connector (Small size JN2)



*3: 22.0 kW motor is IP44.

| | | | | | | | | |
|-------------------------|-------------------------|--|---|--------------------|---|--|--|---------------|
| Basic Specifications | Input power | 100 V | Main circuit | Single phase | 100 V ^{+10 %} / _{-15 %} | to 120 V ^{+10 %} / _{-15 %} | 50 Hz / 60 Hz | |
| | | | Control circuit | Single phase | 100 V ^{+10 %} / _{-15 %} | to 120 V ^{+10 %} / _{-15 %} | 50 Hz / 60 Hz | |
| | | 200 V | Main circuit | A-frame to D-frame | Single/3-phase | 200 V ^{+10 %} / _{-15 %} | to 240 V ^{+10 %} / _{-15 %} | 50 Hz / 60 Hz |
| | | | | E-frame to H-frame | 3-phase | 200 V ^{+10 %} / _{-15 %} | to 240 V ^{+10 %} / _{-15 %} | 50 Hz / 60 Hz |
| | | | Control circuit | A-frame to D-frame | Single phase | 200 V ^{+10 %} / _{-15 %} | to 240 V ^{+10 %} / _{-15 %} | 50 Hz / 60 Hz |
| | | | | E-frame to H-frame | Single phase | 200 V ^{+10 %} / _{-15 %} | to 240 V ^{+10 %} / _{-15 %} | 50 Hz / 60 Hz |
| | Environment | temperature | Ambient temperature: 0 °C to 55 °C (free from freezing) Storage temperature: -20 °C to 65 °C (Max.temperature guarantee: 80 °C for 72 hours free from condensation*1) | | | | | |
| | | humidity | Both operating and storage : 20 %RH to 85 %RH (free from condensation*1) | | | | | |
| | | Altitude | Lower than 1000 m | | | | | |
| | | Vibration | 5.88 m/s ² or less, 10 Hz to 60 Hz | | | | | |
| Control method | | IGBT PWM Sinusoidal wave drive | | | | | | |
| Encoder feedback | | 23-bit (8388608 resolution) absolute encoder, 7-wire serial * When using it as an incremental system (not using multi-turn data), do not connect the battery for absolute encoder. Parameter Pr. 0.15 must be set to "1" (factory settings). | | | | | | |
| External scale feedback | | A/B phase, homing signal differential input. Serial communication is also supported. Manufacturers that support serial communication scale: Fagor Automation S.Coop., HEIDENHAIN, Magnescale Co., Ltd., Mitutoyo Corporation Nidec Instruments Corporation, Renishaw plc | | | | | | |
| Interface connector | Control signal | Input | Each 8 input can be assigned by the parameter. | | | | | |
| | | Output | Each 3 output can be assigned by the parameter. | | | | | |
| | Analog signal | Output | 2 outputs for analog monitors 1 and 2 | | | | | |
| Communication | Pulse signal | Output | Line driver output for encoder pulses (A/B phase signal) or external scale pulses. | | | | | |
| | Realtime Express (RTEX) | Communication for transmission of a real-time operation command, the parameter setting, or the status monitoring. | | | | | | |
| USB | | USB interface to connect to computers (setup support software PANATERM) for parameter setting or status monitoring. | | | | | | |
| Safety terminal | | Terminal to support safety function. | | | | | | |
| Front panel | | (1) 7 segment LED (double digits) (2) Network status LED(LINK,COM) (3) Rotary switch for node address setting (4) Analog monitor output(Analog monitors 1 and 2) | | | | | | |
| Regeneration | | Size A, B, G and H: Without built-in regenerative resistor (use external resistor) Size C to F: Built-in regenerative resistor (External regenerative resistor is also available) | | | | | | |
| Dynamic brake | | A to G frame: built-in H frame: External resistor only | | | | | | |
| Control mode | | (1) Semi-closed control Position control: Profile position control (PP), Cyclic position control (CP) Velocity control: Cyclic velocity control (CV) Torque control: Cyclic torque control (CT) (2) Full-closed control Position control: Profile position control (PP), Cyclic position control (CP) • The two modes, [1] and [2] above are switched by parameters. • Switch PP/CP/CV/CT mode according to the RTEX communication command. | | | | | | |

*1 Air containing water vapor will become saturated with water vapor as the temperature falls, causing dew.

| | | | | | | | | |
|---|--|--|---|---|--|--|--|--|
| Position control | Control input | | Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, Near home position, etc | | | | | |
| | Control output | | Positioning completion etc. | | | | | |
| | Position command input | Input mode | Command type by RTEX command | | | | | |
| | | Smoothing filter | Either a primary delay filter or a FIR type filter can be selected against command input. | | | | | |
| | Damping control | | Available (Up to 3 frequency settings,out of 4 settings in total,can be used simultaneously.) | | | | | |
| | Model type damping filter | | Available (2 filter available used simultaneously) | | | | | |
| | Feed forward function | | Available (speed/torque) | | | | | |
| | Load variation suppression control | | Available | | | | | |
| | Gain 3 switching function | | Available | | | | | |
| | Quadrant glitch inhibit function | | Available | | | | | |
| Two-degree-of-freedom control mode | | Available | | | | | | |
| Motor operable setup function | | Available | | | | | | |
| External scale position information monitor | | Available | | | | | | |
| Other available functions | | Friction torque compensation, Torque limit switching function, Torque saturation protection function, Single-turn absolute function, Continuous rotating absolute encoder function | | | | | | |
| Speed control | Control input | | Positive direction drive inhibit input , Negative direction drive inhibit, Latch signal, etc | | | | | |
| | Control output | | At speed etc. | | | | | |
| | Position command input | Input mode | Command type by RTEX command | | | | | |
| | | Soft start/slowdown function | 0 s to 10 s / 1000 r/min Acceleration and deceleration can be set separately. S-curve acceleration/deceleration is also available. | | | | | |
| | Feed forward function | | Available (torque) | | | | | |
| | Load variation suppression control | | Available | | | | | |
| | Two-degree-of-freedom control mode | | Available (standard type) | | | | | |
| | External scale position information monitor | | Available | | | | | |
| | Other available functions | | Friction torque compensation, Torque limit switching function, Torque saturation protection function, Single-turn absolute function, Continuous rotating absolute encoder function | | | | | |
| | Torque control | Control input | | Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, etc | | | | |
| Control output | | At speed etc. | | | | | | |
| Position command input | | Input mode | Command type by RTEX command | | | | | |
| | | Speed limit function | Speed limit value can be set by parameter. (Switched by RTEX command.) | | | | | |
| External scale position information monitor | | Available | | | | | | |
| Other available functions | | Single-turn absolute function Continuous rotating absolute encoder function | | | | | | |
| Full-closed control | | Control input | | Positive direction drive inhibit input , Negative direction drive inhibit, Latch signal, Near home position , etc | | | | |
| | | Control output | | Positioning completion etc. | | | | |
| | | Position command input | Input mode | Command type by RTEX command | | | | |
| | | | Smoothing filter | Either a primary delay filter or a FIR type filter can be selected against command input. | | | | |
| | Setting range of external scale division/multiplication. | | 1/40 times to 125200 times Although the ratio of the encoder pulse (numerator) and external scale pulse (denominator) can be set anywhere between the range of 1 to 2 ²³ for the numerator and 1 to 2 ³⁰ for the denominator, Please use within the range indicated above. | | | | | |
| | Damping control | | Available(Up to 3 frequency settings,out of 4 settings in total,can be used simultaneously.) | | | | | |
| | Feed forward function | | Available (speed/torque) | | | | | |
| | Load variation suppression control | | Available | | | | | |
| | Gain 3 switching function | | Available | | | | | |
| | Hybrid vibration suppression function | | Available | | | | | |
| Quadrant glitch inhibit function | | Available | | | | | | |
| Two-degree-of-freedom control mode | | Available (standard type) | | | | | | |
| Motor operable setup function | | Available | | | | | | |
| External scale position information monitor | | Available | | | | | | |
| Other available functions | | Friction torque compensation, Torque limit switching function, Torque saturation protection function | | | | | | |
| Common | Electronic gear ratio setting | | Applicable scaling ratio: 1/1000 to 8000 Although any value of 1 to 2 ³⁰ (numerator) and any value of 1 to 2 ³⁰ (denominator) can be used,resulting value should be within the range shown above. | | | | | |
| | Auto tuning | | Identifies the load inertia real-time and automatically sets up the gain that meets the stiffness setting when the motor is running with upper and internal operation commands. | | | | | |
| | Notch filter | | Available (5 filters available) | | | | | |
| | Gain switching function | | Available | | | | | |
| | 2-step torque filter | | Available | | | | | |
| | Position comparison output function | | Available | | | | | |
| | Protective function | | Over-voltage, under-voltage, over-speed, over-load, over-heat, over-current, encoder error, excess position deviation, EEPROM error etc. | | | | | |
| | Alarm data trace back function | | Tracing back of alarm data is available | | | | | |
| | Deterioration diagnosis function | | Available | | | | | |


| | | | | | | | | |
|----------------------|-------------------------|--|---|--------------------|---|--|--|---------------|
| Basic Specifications | Input power | 100 V | Main circuit | Single phase | 100 V ^{+10 %} _{-15 %} | to 120 V ^{+10 %} _{-15 %} | 50 Hz / 60 Hz | |
| | | | Control circuit | Single phase | 100 V ^{+10 %} _{-15 %} | to 120 V ^{+10 %} _{-15 %} | 50 Hz / 60 Hz | |
| | | 200 V | Main circuit | A-frame to D-frame | Single/3-phase | 200 V ^{+10 %} _{-15 %} | to 240 V ^{+10 %} _{-15 %} | 50 Hz / 60 Hz |
| | | | | E-frame, F-frame | 3-phase | 200 V ^{+10 %} _{-15 %} | to 240 V ^{+10 %} _{-15 %} | 50 Hz / 60 Hz |
| | | | Control circuit | A-frame to D-frame | Single phase | 200 V ^{+10 %} _{-15 %} | to 240 V ^{+10 %} _{-15 %} | 50 Hz / 60 Hz |
| | | | | E-frame, F-frame | Single phase | 200 V ^{+10 %} _{-15 %} | to 240 V ^{+10 %} _{-15 %} | 50 Hz / 60 Hz |
| | Environment | temperature | Ambient temperature: 0 °C to 55 °C (free from freezing) Storage temperature: -20 °C to 65 °C (Max.temperature guarantee: 80 °C for 72 hours free from condensation*1) | | | | | |
| | | humidity | Both operating and storage : 20 %RH to 85 %RH (free from condensation*1) | | | | | |
| | | Altitude | Lower than 1000 m | | | | | |
| | | Vibration | 5.88 m/s ² or less, 10 Hz to 60 Hz | | | | | |
| Control method | | IGBT PWM Sinusoidal wave drive | | | | | | |
| Encoder feedback | | 23-bit (8388608 resolution) absolute encoder, 7-wire serial * When using it as an incremental system (not using multi-turn data), do not connect the battery for absolute encoder. Parameter Pr. 0.15 must be set to "1" (factory settings). | | | | | | |
| Interface connector | Control signal | Input | Each 8 input can be assigned by the parameter. | | | | | |
| | | Output | Each 3 output can be assigned by the parameter. | | | | | |
| | Analog signal | Output | 2 outputs for analog monitors 1 and 2 | | | | | |
| | Pulse signal | Output | Line driver output for encoder pulses (A/B phase signal). | | | | | |
| Communication | Realtime Express (RTEX) | Communication for transmission of a real-time operation command, the parameter setting, or the status monitoring. | | | | | | |
| | USB | USB interface to connect to computers (setup support software PANATERM) for parameter setting or status monitoring. | | | | | | |
| Front panel | | (1) 7 segment LED (double digits) (2) Network status LED(LINK,COM) (3) Rotary switch for node address setting (4) Analog monitor output(Analog monitors 1 and 2) | | | | | | |
| Regeneration | | Size A and B: Without built-in regenerative resistor (use external resistor) Size C to F: Built-in regenerative resistor (External regenerative resistor is also available) | | | | | | |
| Dynamic brake | | A to F frame: built-in | | | | | | |
| Control mode | | (1) Semi-closed control Position control: Profile position control (PP), Cyclic position control (CP) Velocity control: Cyclic velocity control (CV) Torque control: Cyclic torque control (CT) • Switch PP/CP/CV/CT mode according to the RTEX communication command. | | | | | | |

*1 Air containing water vapor will become saturated with water vapor as the temperature falls, causing dew.

| | | | | | | | |
|------------------------------------|-------------------------------------|--|--|--|--|--|--|
| Position control | Control input | | Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, Near home position , etc | | | | |
| | Control output | | Positioning completion etc. | | | | |
| | Position command input | Input mode | Command type by RTEX command | | | | |
| | | Smoothing filter | Either a primary delay filter or a FIR type filter can be selected against command input. | | | | |
| | Damping control | | Available(Up to 3 frequency settings,out of 4 settings in total,can be used simultaneously.) | | | | |
| | Model type damping filter | | Available(2 filter available used simultaneously) | | | | |
| | Feed forward function | | Available (speed/torque) | | | | |
| | Load variation suppression control | | Available | | | | |
| | Gain 3 switching function | | Available | | | | |
| | Quadrant glitch inhibit function | | Available | | | | |
| Two-degree-of-freedom control mode | | Available | | | | | |
| Motor operatable setup function | | Available | | | | | |
| Other available functions | | Friction torque compensation, Torque limit switching function, Torque saturation protection function, Single-turn absolute function, Continuous rotating absolute encoder function | | | | | |
| Speed control | Control input | | Positive direction drive inhibit input , Negative direction drive inhibit, Latch signal, etc | | | | |
| | Control output | | At speed etc. | | | | |
| | Position command input | Input mode | Command type by RTEX command | | | | |
| | | Soft start/slowdown function | 0 s to 10 s / 1000 r/min Acceleration and deceleration can be set separately. S-curve acceleration/deceleration is also available. | | | | |
| | Feed forward function | | Available (torque) | | | | |
| | Load variation suppression control | | Available | | | | |
| Two-degree-of-freedom control mode | | Available (standard type) | | | | | |
| Other available functions | | Friction torque compensation, Torque limit switching function, Torque saturation protection function, Single-turn absolute function, Continuous rotating absolute encoder function | | | | | |
| Torque control | Control input | | Positive direction drive inhibit input, Negative direction drive inhibit, Latch signal, etc | | | | |
| | Control output | | At speed etc. | | | | |
| | Position command input | Input mode | Command type by RTEX command | | | | |
| | | Speed limit function | Speed limit value can be set by parameter. (Switched by RTEX command.) | | | | |
| Other available functions | | Single-turn absolute function Continuous rotating absolute encoder function | | | | | |
| Common | Electronic gear ratio setting | | Applicable scaling ratio: 1/1000 to 8000 Although any value of 1 to 2 ³⁰ (numerator) and any value of 1 to 2 ³⁰ (denominator) can be used,resulting value should be within the range shown above. | | | | |
| | Auto tuning | | Identifies the load inertia real-time and automatically sets up the gain that meets the stiffness setting when the motor is running with upper and internal operation commands. | | | | |
| | Notch filter | | Available (5 filters available) | | | | |
| | Gain switching function | | Available | | | | |
| | 2-step torque filter | | Available | | | | |
| | Position comparison output function | | Available | | | | |
| | Protective function | | Over-voltage, under-voltage, over-speed, over-load, over-heat, over-current, encoder error, excess position deviation, EEPROM error etc. | | | | |
| | Alarm data trace back function | | Tracing back of alarm data is available | | | | |
| Deterioration diagnosis function | | Available | | | | | |

* All dimensions shown in this catalog are for the A6NF series, but outer dimensions are the same as the A6NE series.

A-frame




| A-frame: Connector of driver side | | | Multifunction type | Basic type |
|-----------------------------------|-----------------------------------|---------------------------------|--------------------|------------|
| Connector XA | S05B-F32SK-GGXR (or equivalent) | J.S.T. Mfg. Co., Ltd. | ● | ● |
| Connector XB | S06B-F32SK-GGXR (or equivalent) | J.S.T. Mfg. Co., Ltd. | ● | ● |
| Connector X1 | UB-M5BR-S14-4S (or equivalent) | J.S.T. Mfg. Co., Ltd. | ● | ● |
| Connector X3 | CIF-HS08SS-071-TB (or equivalent) | J.S.T. Mfg. Co., Ltd. | ● | - |
| Connector X2A | MOD-WRJ88LY1G-TP+ (or equivalent) | HTK | ● | ● |
| Connector X2B | MOD-WRJ88LY1G-TP+ (or equivalent) | HTK | ● | ● |
| Connector X4 | DF02R026NA2 (or equivalent) | Japan Aviation Electronics Ind. | ● | ● |
| Connector X5 | MUF-RS10SK-GKX-TB (or equivalent) | J.S.T. Mfg. Co., Ltd. | ● | - |
| Connector X6 | 3E106-2230KV (or equivalent) | 3M Japan | ● | ● |
| Connector X7 | 533984005 (5pin) | Molex | ● | ● |

Mass: 0.8 kg

<Attached to the driver>

| Connector of power and motor side | | |
|-----------------------------------|------------------|-----------------------|
| Connector XA | 05JFAT-SAXGGKK-A | J.S.T. Mfg. Co., Ltd. |
| Connector XB | 06JFAT-SAXGGKK-A | J.S.T. Mfg. Co., Ltd. |


C-frame



* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

Mass: 1.6 kg


B-frame



* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

Mass: 1.0 kg

D-frame (200 V)



* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

Mass: 2.1 kg

E-frame (200 V)

Unit [mm]

X1 : USB connector
 X3 : Safety function connector
 X2A : RTEX RX connector
 X2B : RTEX TX connector
 X4 : I/O connector
 X5 : Feedback scale connector
 X6 : Encoder connector
 X7 : For analog monitor signal connection

XA : ① Main power input terminals
 ② Control power input terminals
 XB : Terminals for motor connection
 XC : Terminals for external regenerative resistor

2-M4 #6 flat head screw

Mounting bracket (If re-positioned from front end)

196.5

85 (Mounting dimensions)

50

2-5.2

For mounting

198 (Mounting dimensions)

168

70

2.5

3.5

160

2.5

33

70

Name plate

52

18

216

Mounting bracket (If re-positioned from front end)

2-M4 #6 flat head screw

Direction of air flowing to the internal cooling fan

Ground screw

| E-frame: Connector of driver side | | |
|-----------------------------------|------------------------------------|-----------------------|
| Connector XA | S05B-JTSLSK-GSANXR (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XB | S03B-JTSLSK-GSANXR (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XC | S04B-JTSLSS-GSANXR (or equivalent) | J.S.T. Mfg. Co., Ltd. |

<Attached to the driver>

| E-frame: Connector of power and motor side | | |
|--|---------------------------------|-----------------------|
| Connector XA | 05JFAT-SAXGSA-L (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XB | 03JFAT-SAXGSA-L (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XC | 04JFAT-SAXGSA-L (or equivalent) | J.S.T. Mfg. Co., Ltd. |

* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

Mass: 2.7 kg

F-frame (200 V)

Unit [mm]

X1 : USB connector
 X3 : Safety function connector
 X2A : RTEX RX connector
 X2B : RTEX TX connector
 X4 : I/O connector
 X5 : Feedback scale connector
 X6 : Encoder connector
 X7 : For analog monitor signal connection

① Main power input terminals
 ② Control power input terminals
 ③ Terminals for external regenerative resistor
 ④ Terminals for motor connection

2-M4 #6 flat head screw

Mounting bracket (If re-positioned from front end)

219.5

100 (Mounting dimensions)

130

2-5.2

For mounting

250 (Mounting dimensions)

220

20

2.5

3.5

169

47

20

Name plate

2.5

67

169

Mounting bracket (If re-positioned from front end)

2-M4 #6 flat head screw

Direction of air flowing to the internal cooling fan

①

②

③

④

100 (Mounting dimensions)

2-5.2

100

2-5.2

For mounting

2.5

47

169

2-M4 #6 flat head screw

Mass: 5.2 kg

G-frame (200 V) (A6NE series are not available.)

Unit [mm]

X1 : USB connector
 X3 : Safety function connector
 X2A : RTEX RX connector
 X2B : RTEX TX connector
 X4 : I/O connector
 X5 : Feedback scale connector
 X6 : Encoder connector
 XE : Connector for external dynamic brake signal
 XS : Built-in dynamic brake switch

X7 : For analog monitor signal connection

Control power input terminals

Main power input terminals

Terminals for external regenerative resistor

Terminals for motor connection

3-M4 #6 flat head screw

3-M4 #6 flat head screw

Direction of air flowing to the internal cooling fan

184

90 (Mounting dimensions)

47

2-6.2

For mounting

257

50

2.5

Mounting bracket (If re-positioned from front end)

197

56

50

Name plate

2.5

106

199

Mounting bracket (If re-positioned from front end)

3-M4 #6 flat head screw


3-M4 #6 flat head screw

| Connector of driver side | Control side (customer prepares) |
|--------------------------------------|----------------------------------|
| Connector XE : 5569-04A2-210 (Molex) | Connector : 5557-04R-210 (Molex) |
| | Pin : 5556PBT |

* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

Mass: 8.2 kg


H-frame (200 V) (A6NE series are not available.)



Refer to P.29 to P.42 for other options than the interface cable and interface connector kit.

Cable for Interface

Part No. DVOP0800 Cable length 2 m, core wire AWG 26 is connected.



• Table for wiring

| Pin No. | Signal name | color | Pin No. | Signal name | color | Pin No. | Signal name | color |
|---------|-------------|-----------------|---------|-------------|-----------------|---------|-------------|-----------------|
| 1* | BRK-OFF+ | Orange (Red1) | 10* | HOME | Pink (Black1) | 19 | OB-/OCMP2- | Pink (Red2) |
| 2* | BRK-OFF- | Orange (Black1) | 11* | EXT2 | Orange (Red2) | 20 | OB+/OCMP2+ | Pink (Black2) |
| 3* | ALM+ | Gray (Red1) | 12* | EXT3 | Orange (Black2) | 21 | OCMP3+ | Orange (Red3) |
| 4* | ALM- | Gray (Black1) | 13* | SI-MON4 | Gray (Red2) | 22 | OCMP3- | Gray (Red3) |
| 5* | SI-MON5 | White (Red1) | 14 | BTP-I | Gray (Black2) | 23 | - | Gray (Black3) |
| 6 | I-COM | White (Black1) | 15 | BTN-I | White (Red2) | 24 | - | White (Red3) |
| 7* | POT | Yellow (Red1) | 16 | GND | White (Black2) | 25* | EX-OUT1+ | White (Black3) |
| 8* | NOT | Yellow (Black1) | 17 | OA+/OCMP1+ | Yellow (Red2) | 26* | EX-OUT1- | Orange (Black3) |
| 9* | SI-MON1 | Pink (Red1) | 18 | OA-/OCMP1- | Yellow (Black2) | | | |

The signals allocated to the pin No. with "*" in the table are factory default.

<Remarks>

Color designation of the cable e.g.) Pin-1 Cable color : Orange (Red1) : One red dot on the cable

<Caution>

The shield of this cable is not connected to the terminal of the connector.
The shielded wire of the cable is connected to the connector shell of the cable, and is connected to the FG via the connector shell on the Driver side. When connecting the shielded wire of the cable to GND, use the connector kit DVOP0770 for the interface. At that time, please note that if you connect the shield and the connector shell on the cable side and process it, FG and GND will be connected.


Connector Kit for Interface

Part No. DVOP0770

• Components

| Title | Part No. | Number | Manufacturer | Note |
|-----------------|----------------|--------|--------------------------|---------------------|
| Connector | 10126-3000PE | 1 | 3M Japan (or equivalent) | For CN X4 (26-pins) |
| Connector cover | 10326-52AO-008 | 1 | | |

• Pin disposition: Connector X4 (26 pins) (viewed from the soldering side)



<Remarks>

1. Check the stamped pin-No. on the connector body while making a wiring.
2. For the symbols representing the signal names or the functions of the signals in the figure above, refer to the operation manual.

Servo driver with EtherCAT open network

EtherCAT  **EtherCAT**
AC servo motor & driver

MINAS A6B Series Special Order Product



A6BE Series
A6BF Series

Quickly

Response frequency 3200 Hz & communication rate 100 Mbps enable fast and highly accurate operation.
Configurable even for motors with a maximum rotating speed 6500 r/min.*

* MDMF and MQMF types with a maximum wattage 400 W

Wisely

New algorithm “Two-degree-of-freedom control method” is used to improve machining accuracy and productivity.

Easily

Easy and speedy set-up with set-up support software “PANATERM”

- Fully-featured EtherCAT application (7 control modes, 32 origin-return modes, 2 synchronous modes, and an asynchronous mode.)
- Capable of system upgrade with various slaves.
- Capable of establishing PC-based systems without needing dedicated hardware.
- Planned to pass official EtherCAT Conformance Test.
- A6BF with safety I/F*2 corresponding to international standard, and A6BL/A6BM supporting linear motors

*2 : IEC61800-5-2 STO, IEC61508 SIL3.

* The EtherCAT is a registered trademark of patented technology licensed from Beckhoff Automation GmbH in Germany.

INDEX

| | |
|---------------------------|-----|
| Features..... | 369 |
| Driver appearance..... | 371 |
| System configuration..... | 371 |
| Driver..... | 372 |
| Dimensions of driver..... | 372 |

A6 Series
A6N Series
A6B Series
Special Order Product
Information

MINAS A6B Series Model Designation Special Order Product

For more information, please visit our website or request to our distributors separately.

Servo Driver

M A D L N 1 5 B E * * * Special specifications

| ① Frame symbol <table border="1"> <thead> <tr> <th>Symbol</th> <th>Frame</th> <th>Symbol</th> <th>Frame</th> </tr> </thead> <tbody> <tr> <td>MAD</td> <td>A-Frame</td> <td>MED</td> <td>E-Frame</td> </tr> <tr> <td>MBD</td> <td>B-Frame</td> <td>MFD</td> <td>F-Frame</td> </tr> <tr> <td>MCD</td> <td>C-Frame</td> <td>MGD</td> <td>G-Frame</td> </tr> <tr> <td>MDD</td> <td>D-Frame</td> <td>MHD</td> <td>H-Frame</td> </tr> </tbody> </table> | | Symbol | Frame | Symbol | Frame | MAD | A-Frame | MED | E-Frame | MBD | B-Frame | MFD | F-Frame | MCD | C-Frame | MGD | G-Frame | MDD | D-Frame | MHD | H-Frame | ④ Max. current rating <table border="1"> <thead> <tr> <th>Symbol</th> <th>Current rating</th> <th>Symbol</th> <th>Current rating</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>6 A</td> <td>9</td> <td>80 A</td> </tr> <tr> <td>1</td> <td>8 A</td> <td>A</td> <td>100 A</td> </tr> <tr> <td>2</td> <td>12 A</td> <td>B</td> <td>120 A</td> </tr> <tr> <td>3</td> <td>22 A</td> <td>C</td> <td>160 A</td> </tr> <tr> <td>4</td> <td>24 A</td> <td>E</td> <td>240 A</td> </tr> <tr> <td>5</td> <td>40 A</td> <td>F</td> <td>360 A</td> </tr> <tr> <td>8</td> <td>60 A</td> <td></td> <td></td> </tr> </tbody> </table> | | Symbol | Current rating | Symbol | Current rating | 0 | 6 A | 9 | 80 A | 1 | 8 A | A | 100 A | 2 | 12 A | B | 120 A | 3 | 22 A | C | 160 A | 4 | 24 A | E | 240 A | 5 | 40 A | F | 360 A | 8 | 60 A | | | ⑥ I/f specifications | | ⑦ Classification of type*1 <table border="1"> <thead> <tr> <th>Symbol (specification)</th> <th>Symbol</th> <th>Specification</th> </tr> </thead> <tbody> <tr> <td rowspan="4">B (EtherCAT)</td> <td>E</td> <td>Standard for rotary motor Special Order Product</td> </tr> <tr> <td>F</td> <td>Multifunction for rotary motor Special Order Product</td> </tr> <tr> <td>L</td> <td>Standard for linear/ DD motor Special Order Product</td> </tr> <tr> <td>M</td> <td>Multifunction for linear/ DD motor Special Order Product</td> </tr> </tbody> </table> | | Symbol (specification) | Symbol | Specification | B (EtherCAT) | E | Standard for rotary motor Special Order Product | F | Multifunction for rotary motor Special Order Product | L | Standard for linear/ DD motor Special Order Product | M | Multifunction for linear/ DD motor Special Order Product |
|---|-----------------------------|---|----------------|--------|-----------------------------|---|--------------------------|--------|----------------|-----|--------------------|-----|---------------|-----|----------------------|---|---------|-----|---------|-----|---------|---|--|--------|----------------|--------|----------------|---|-----|---|------|---|-----|---|-------|---|------|---|-------|---|------|---|-------|---|------|---|-------|---|------|---|-------|---|------|--|--|-----------------------------|--|--|--|------------------------|--------|---------------|--------------|---|--|---|---|---|--|---|---|
| Symbol | Frame | Symbol | Frame | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| MAD | A-Frame | MED | E-Frame | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| MBD | B-Frame | MFD | F-Frame | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| MCD | C-Frame | MGD | G-Frame | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| MDD | D-Frame | MHD | H-Frame | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Symbol | Current rating | Symbol | Current rating | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 0 | 6 A | 9 | 80 A | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1 | 8 A | A | 100 A | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 2 | 12 A | B | 120 A | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 3 | 22 A | C | 160 A | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 4 | 24 A | E | 240 A | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 5 | 40 A | F | 360 A | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 8 | 60 A | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Symbol (specification) | Symbol | Specification | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| B (EtherCAT) | E | Standard for rotary motor Special Order Product | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | F | Multifunction for rotary motor Special Order Product | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | L | Standard for linear/ DD motor Special Order Product | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | M | Multifunction for linear/ DD motor Special Order Product | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| ② Series <table border="1"> <thead> <tr> <th>Symbol</th> <th>Series name</th> </tr> </thead> <tbody> <tr> <td>L</td> <td>A6 Family</td> </tr> </tbody> </table> | | Symbol | Series name | L | A6 Family | ⑤ Supply voltage specifications <table border="1"> <thead> <tr> <th>Symbol</th> <th>Specifications</th> </tr> </thead> <tbody> <tr> <td>1</td> <td>Single phase 100 V</td> </tr> <tr> <td>3</td> <td>3-phase 200 V</td> </tr> <tr> <td>5</td> <td>Single/3-phase 200 V</td> </tr> </tbody> </table> | | Symbol | Specifications | 1 | Single phase 100 V | 3 | 3-phase 200 V | 5 | Single/3-phase 200 V | *1 Standard type (with a part number ending in E or L) has no safety function. Multi-function type (with a part number ending in F or M) has a safety function. | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Symbol | Series name | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| L | A6 Family | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Symbol | Specifications | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1 | Single phase 100 V | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 3 | 3-phase 200 V | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 5 | Single/3-phase 200 V | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| ③ Safety Function*1 <table border="1"> <thead> <tr> <th>Symbol</th> <th>Specifications</th> </tr> </thead> <tbody> <tr> <td>N</td> <td>without the safety function</td> </tr> <tr> <td>T</td> <td>with the safety function</td> </tr> </tbody> </table> | | Symbol | Specifications | N | without the safety function | T | with the safety function | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Symbol | Specifications | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| N | without the safety function | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| T | with the safety function | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |

C-frame

Unit [mm]

X1 : USB connector
X3 : Safety function connector
X2A : Connector X2A: IN for EtherCAT
X2B : Connector X2B: OUT for EtherCAT
X4 : I/O connector
X5 : Feedback scale connector
X6 : Encoder connector
X7 : For analog monitor signal connection

XA : ① Main power input terminals
② Control power input terminals
XB : ① Terminals for external regenerative resistor
② Terminals for motor connection

2-M4 #6 flat head screw

For mounting

Front Panel

Mounting bracket (Option)

Name plate

Mounting bracket (Option)

Base mount type (Standard: Back-end mounting)

Rack mount type (Option: Front-end mounting)

2-M4 #6 flat head screw

Mass: 1.6 kg

* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

E-frame (200 V)

Unit [mm]

X1 : USB connector
X3 : Safety function connector
X2A : Connector X2A: IN for EtherCAT
X2B : Connector X2B: OUT for EtherCAT
X4 : I/O connector
X5 : Feedback scale connector
X6 : Encoder connector
X7 : For analog monitor signal connection

XA : ① Main power input terminals
② Control power input terminals
XB : Terminals for motor connection
XC : Terminals for external regenerative resistor

2-M4 #6 flat head screw

Mounting bracket (If re-positioned from front end)

Mounting bracket (If re-positioned from front end)

Mounting bracket (If re-positioned from front end)

2-M4 #6 flat head screw

Mass: 2.7 kg

* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

| E-frame: Connector of driver side | | |
|-----------------------------------|------------------------------------|-----------------------|
| Connector XA | S05B-JTSLSK-GSANXR (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XB | S03B-JTSLSK-GSANXR (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XC | S04B-JTSLSS-GSANXR (or equivalent) | J.S.T. Mfg. Co., Ltd. |

| E-frame: Connector of power and motor side | | |
|--|---------------------------------|-----------------------|
| Connector XA | 05JFAT-SAXGSA-L (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XB | 03JFAT-SAXGSA-L (or equivalent) | J.S.T. Mfg. Co., Ltd. |
| Connector XC | 04JFAT-SAXGSA-L (or equivalent) | J.S.T. Mfg. Co., Ltd. |

<Attached to the driver>

D-frame (200 V)

Unit [mm]

X1 : USB connector
X3 : Safety function connector
X2A : Connector X2A: IN for EtherCAT
X2B : Connector X2B: OUT for EtherCAT
X4 : I/O connector
X5 : Feedback scale connector
X6 : Encoder connector
X7 : For analog monitor signal connection

XA : ① Main power input terminals
② Control power input terminals
XB : ① Terminals for external regenerative resistor
② Terminals for motor connection

2-M4 #6 flat head screw

For mounting

Front Panel

Mounting bracket (Option)

Name plate

Mounting bracket (Option)

Base mount type (Standard: Back-end mounting)

Rack mount type (Option: Front-end mounting)

2-M4 #6 flat head screw

Mass: 2.1 kg

* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

F-frame (200 V)

Unit [mm]

X1 : USB connector
X3 : Safety function connector
X2A : Connector X2A: IN for EtherCAT
X2B : Connector X2B: OUT for EtherCAT
X4 : I/O connector
X5 : Feedback scale connector
X6 : Encoder connector
X7 : For analog monitor signal connection

① Main power input terminals
② Control power input terminals
③ Terminals for external regenerative resistor
④ Terminals for motor connection

2-M4 #6 flat head screw

Mounting bracket (If re-positioned from front end)

Mounting bracket (If re-positioned from front end)

Mounting bracket (If re-positioned from front end)


2-M4 #6 flat head screw

Mass: 5.2 kg

* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

G-frame (200 V) (A6BE series are not available.)

Unit [mm]




| Connector of driver side | Controlor side (customer prepares) |
|--------------------------------------|---|
| Connector XE : 5569-04A2-210 (Molex) | Connector : 5557-04R-210 (Molex) Pin : 5556PBT |

* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

Mass: 8.2 kg

H-frame (200 V) (A6BE series are not available.)

Unit [mm]



* For connectors X1 to X7, refer to the list provided in the A-frame table because both frames use the same connectors.

Mass:
MHDLTE3BF/ 14.2 kg
MHDLTF3BF/ 15.2 kg